



Delco Remy

DIVISION OF GENERAL MOTORS • ANDERSON, INDIANA

SERVICE TEST SPECIFICATIONS

For Generators Released 1978-1986

BULLETIN NO. **1G-188**

DATE 3-1-86

19 PAGES PAGE 1

Supplements Bulletins

1G-187 1964-1977

1G-186 1956-1963

1G-180, 1G-185 Prior to 1956

Supersedes 1G-188 (3-1-85)

The specifications in this bulletin may be used when testing the performance of Delco Remy generators. Testing procedures are covered in the applicable Service Bulletin, listed in column 4 and identified on page 2.

SYSTEM GROUND (Column 3, page 2)

When connected to a battery, the ground polarity of the generator must be the same as the ground polarity of the battery. "N" denotes negative ground, "P" denotes positive ground.

FIELD RESISTANCE IN OHMS (Column 7, page 2)

A high ohmmeter reading indicates excessive resistance, and a low reading indicates shorted field windings, which can cause regulator failure. Always check field resistance when replacing a defective regulator.

FIELD CURRENT IN AMPERES (Column 8, page 2)

A low ammeter reading indicates excessive resistance, and a high reading indicates shorted field windings, which can cause regulator failure. Always check field current when replacing a defective regulator.

COLD OUTPUT IN AMPERES (Columns 10 and 11, page 2)

These columns give amperes output at specified speeds *with the generator at a temperature of 27° C (80° F)*, with the generator hot output given in column 12. If no value is given in column 12, these values in columns 10 and 11 are RATED HOT OUTPUT IN AMPERES, see section below.

RATED HOT OUTPUT IN AMPERES (Column 12, page 2)

This column gives maximum amperes output *with the generator temperature stabilized (HOT) at maximum amperes output* in an ambient (room) temperature of 27° C (80° F). *When no value is given in column 12, the RATED HOT OUTPUT is given in columns 10 and 11.*

GENERATORS

1. 2. 3. 4. 5. 6. 7. 8. 9. 10. 11. 12.

- 1. Delcotron Generator Model
Delcotron Generator Modell
Alternateur Delcotron Modèle
Alternador Delcotron Modelo
- 2. Series
Serie
Séries
Serie
- 3. Type Grd.
Typ Masse
Type de masse
Tipo
- 4. Service Bulletin
Kundenienst Technische Information
Bulletin de service
Boletín de servicio
- 5. Rotation Viewing D.E.
Drehrichtung
Sens de rotation (coté entrainement)
Sentido de rotacion
- 6. Spec. No.
Spez. Nr.
Spec. No.
No. de especificacion
- 7. Field Ohms
Feldohm
Résistance dechamps (ohms)
Resistencia de campo (ohmios)
- 8. Field Current (80°F)
Erregerstrom
Courant de champs
Corriente de campo
(80°F. = 27°C.)
- 9. Specified Volts
Spannung lt. Spez.
Tension Spécifiée
Tension especificada voltios
- 10. Cold Output
Leistung in kaltem Zustand
Débit à froid
Potencia en frio
- 11. Approx. RPM
U/Min ca.
Approx. RPM
- 12. Rated Hot Output (amps)
Nennleistung in heißem Zustand
Débit moyen à chaud
Potencia nominal en caliente

| 1. Delcotron Generator Model | 2. Series | 3. Type Grd. | 4. Service Bulletin | 5. Rotation Viewing D E | 6. Spec No. | 7. Field Ohms (80°F) | 8. FIELD CURRENT (80°F) | | 9. Specified Volts | 10. COLD OUTPUT | | | | 12. Rated Hot Output (Amps) |
|------------------------------|-----------|--------------|---------------------|-------------------------|-------------|----------------------|-------------------------|-------|--------------------|-----------------|------------|----------|------------|-----------------------------|
| | | | | | | | Amps | Volts | | Amps | Approx RPM | 11. Amps | Approx RPM | |
| 1100089 | 27SI | 200 N | 1G-270 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1100090 | 27SI | 200 N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1100091 | 27SI | 200 N | 1G-270 | EITHER | 4593 | 2.2-2.7 | 4.5-5.5 | 12 | 12 | 73 | 2850 | 83 | 7000 | 100 |
| 1100092 | 10SI | 102 N | 1G-266 | EITHER | 4544 | 2.2-2.4 | .50-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1100093 | 27SI | 200 N | 1G-270 | EITHER | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1100094 | 27SI | 205 N | 1G-266 | EITHER | 4594 | 2.4-2.7 | 4.4-4.9 | 12 | 14 | 55 | 2000 | 68 | 7000 | 65 |
| 1100095 | 27SI | 205 N | 1G-266 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1100096 | 27SI | 205 N | 1G-266 | EITHER | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1100109 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100110 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100111 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100113 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100114 | 10SI | 136 N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1100115 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100116 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100119 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100120 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100121 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100122 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100123 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100124 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100125 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100127 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100129 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100130 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100131 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100132 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100133 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100134 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100135 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100138 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100139 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100140 | 10SI | 100 N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100141 | 10SI | 100 N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100142 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100143 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100145 | 10SI | 100 N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100146 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100148 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100149 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100150 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100151 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100152 | 10SI | 100 N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100153 | 10SI | 100 N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100154 | 10SI | 100 N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |

† At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|------------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1100155 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100156 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100158 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100159 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100162 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100163 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100164 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100165 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100166 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100167 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100168 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100169 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100170 | 10SI | 116 | N | 1G-269 | EITHER | 7205 | 2.4-3.0 | 4.0-5.0 | 12 | † | 34 | 2000 | 61 | 7000 | 61 |
| 1100171 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-3.0 | 4.0-5.0 | 12 | † | 27 | 2000 | 72 | 7000 | 72 |
| 1100172 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100173 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100174 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100175 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100176 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100177 | 27SI | 200 | N | 1G-266 | EITHER | 4594 | 2.3-2.5 | 4.8-5.2 | 12 | † | 55 | 2000 | 68 | 7000 | 65 |
| 1100178 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100179 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100180 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100181 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100182 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100183 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100184 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100186 | 10SI | 110 | N | 1G-267 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100187 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100188 | 27SI | 200 | N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1100189 | 27SI | 200 | N | 1G-270 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1100190 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100191 | 15SI | 100 | N | 1G-266 | CW | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100192 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100193 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100194 | 15SI | 100 | N | 1G-266 | CW | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100195 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100196 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100197 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100198 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100199 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100200 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100201 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100202 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100203 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100204 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100205 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100206 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100207 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100208 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100209 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100210 | 27SI | 202 | N | 1G-270 | EITHER | 4548 | 24-40 | 6-1.0 | 24 | † | 20 | 2000 | 32 | 5000 | 30 |
| 1100211 | 27SI | 200 | N | 1G-270 | EITHER | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1100212 | 27SI | 200 | N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1100213 | 27SI | 200 | N | 1G-270 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1100214 | 27SI | 200 | P | 1G-270 | EITHER | 4561 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1100215 | 27SI | 200 | N | 1G-270 | EITHER | 4593 | 2.2-2.7 | 4.5-5.5 | 12 | † | 73 | 2850 | 83 | 7000 | 100 |
| 1100216 | 27SI | 205 | N | 1G-266 | EITHER | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1100217 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100218 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100219 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100220 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100221 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1100222 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100223 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100224 | 15SI | 100 | N | 1G-266 | EITHER | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100225 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100226 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100227 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100228 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd. | Service Bulletin | Rotation Viewing D. E. | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|------|------------------|------------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1100229 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100230 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100231 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100232 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100233 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100234 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100235 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100236 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100237 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100238 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100239 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100240 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100241 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100242 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100243 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100244 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100245 | 12SI | 100 | N | 1G-266 | EITHER | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100246 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100247 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100248 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100249 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100250 | 12SI | 100 | N | 1G-266 | EITHER | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100252 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100253 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100254 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100255 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100256 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100257 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100258 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100259 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100260 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100261 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100262 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100263 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100264 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100265 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100266 | 10SI | 100 | N | 1G-266 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100267 | 10SI | 110 | N | 1G-278 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100268 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1100269 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1100270 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100271 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100272 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100273 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100274 | 27SI | 200 | N | 1G-270 | EITHER | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1100280 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100281 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100282 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100283 | 15SI | 100 | N | 1G-266 | CW | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100284 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100285 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100286 | 15SI | 100 | N | 1G-266 | CW | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100287 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100288 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100289 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1100290 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100291 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100293 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100294 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1100295 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1100296 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1100297 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1100298 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100299 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1100300 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1101034 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101035 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101036 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101037 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101038 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron
Generator
Model | Series | Type | Grd | Service
Bulletin | Rotation
Viewing
D. E. | Spec
No | Field
Ohms
(80°F) | FIELD CURRENT
(80°F) | | Specified
Volts | COLD OUTPUT | | | | Rated
Hot
Output
(Amps) |
|---------------------------------|--------|------|-----|---------------------|------------------------------|------------|-------------------------|-------------------------|-------|--------------------|-------------|---------------|------|---------------|----------------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx
RPM | Amps | Approx
RPM | |
| 1101039 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101040 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101041 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101042 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101043 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101044 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101045 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101046 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101047 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101048 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101049 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101050 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1101058 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101059 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1101060 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101061 | 27SI | 100 | N | 1G-266 | EITHER | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101062 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101063 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101064 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101065 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101066 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101067 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101068 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101070 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101071 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101073 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101074 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101075 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101076 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101077 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101078 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101079 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101080 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101081 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101082 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101083 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101084 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101085 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101086 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101087 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101088 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101090 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101091 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1101092 | 15SI | 100 | N | 1G-266 | EITHER | 4586 | 2.4-2.7 | 4.4-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101093 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101094 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101095 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101096 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101097 | 15SI | 100 | N | 1G-266 | EITHER | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101098 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101099 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101100 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | 70 |
| 1101101 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | 70 |
| 1101102 | 27SI | 100 | N | 1G-266 | CW | 4594 | 2.4-2.7 | 4.4-4.9 | 12 | 14 | 55 | 2000 | 68 | 7000 | 65 |
| 1101103 | 27SI | 200 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101104 | 27SI | 200 | N | 1G-270 | CW | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1101105 | 27SI | 200 | N | 1G-270 | CW | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1101106 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 70 |
| 1101107 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 70 |
| 1101109 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1101110 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 70 |
| 1101111 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 70 |
| 1101112 | 17SI | 100 | N | 1G-266 | CW | 7238 | 2.4-2.8 | 4.2-5.0 | 12 | † | 47 | 1600 | 97 | 6500 | 70 |
| 1101113 | 17SI | 100 | N | 1G-266 | CW | 7238 | 2.4-2.8 | 4.2-5.0 | 12 | † | 47 | 1600 | 97 | 6500 | 70 |
| 1101114 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | 70 |
| 1101115 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | 70 |
| 1101117 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | 70 |
| 1101118 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101119 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 70 |
| 1101120 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 70 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| DeLcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D E | Spec. No | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|----------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1101121 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101122 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101123 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101124 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101125 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101126 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101127 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1101128 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101129 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 1101130 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 1101131 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101132 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101133 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 1101134 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | |
| 1101135 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101136 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101137 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101138 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101139 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101140 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101141 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101142 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101143 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101144 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101145 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101146 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101147 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101148 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101149 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101150 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101151 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101152 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101153 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101154 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101155 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-2.8 | 4.2-5.0 | 12 | † | 19 | 1600 | 37 | 6500 | |
| 1101156 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | |
| 1101157 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 78 | 6500 | |
| 1101158 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101159 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-2.8 | 4.2-5.0 | 12 | † | 22 | 1600 | 42 | 6500 | |
| 1101160 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101161 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101162 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101163 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101164 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 1101165 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101166 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101167 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101168 | CS121 | 100 | N | 1G-290 | CW | 7259 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 1101169 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101170 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101171 | CS121 | 100 | N | 1G-290 | CW | 7259 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 1101172 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101173 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101174 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101175 | CS121 | 100 | N | 1G-290 | CW | 7259 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 1101176 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101177 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1101178 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1101179 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101180 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101181 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1101182 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 1101183 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 1101184 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1101185 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.6 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 1101186 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101187 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1101188 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101189 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1101190 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |

† At maximum operating speed.

‡ Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec. No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) | |
|---------------------------|--------|------|-----|------------------|------------------------|-----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|-----------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | | |
| 1101191 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 105
40 | |
| 1101192 | 10SI | 116 | N | 1G-269 | CW | 4582 | 2.4-2.8 | 4.2-5.0 | 12 | † | 22 | 1600 | 42 | 6500 | | |
| 1101193 | 10SI | 116 | N | 1G-269 | CW | 4533 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 63 | 6500 | | |
| 1101194 | 15SI | 116 | N | 1G-269 | CW | 4595 | 2.6-3.0 | 4.0-4.7 | 12 | † | 55 | 2000 | 100 | 5000 | | |
| 1101195 | 10SI | 116 | N | 1G-269 | CW | 4545 | 6.8-7.2 | 3.3-3.6 | 24 | † | 25 | 2600 | 41 | 7000 | | |
| 1101196 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | 40
105 | |
| 1101197 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | | |
| 1101198 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | | |
| 1101199 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | | |
| 1101200 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101201 | 10SI | 116 | N | 1G-269 | CW | 4558 | 2.4-2.8 | 4.2-5.0 | 12 | † | 22 | 1600 | 42 | 6500 | | |
| 1101202 | 10SI | 116 | N | 1G-269 | CW | 4533 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 63 | 6500 | | |
| 1101203 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 63 | 6500 | | |
| 1101204 | 10SI | 116 | N | 1G-269 | EITHER | 4545 | 6.8-7.2 | 3.3-3.6 | 24 | † | 25 | 2600 | 41 | 7000 | | |
| 1101205 | 15SI | 116 | N | 1G-269 | EITHER | 4595 | 2.6-3.0 | 4.0-4.7 | 12 | † | 55 | 2000 | 100 | 5000 | | |
| 1101206 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | | 40
105 |
| 1101207 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | | |
| 1101208 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101209 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101210 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101211 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101212 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101213 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101214 | 17SI | 100 | N | 1G-266 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101215 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101216 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101217 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101218 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | | |
| 1101219 | CS121 | 100 | N | 1G-290 | CW | 7265 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | | |
| 1101220 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | | |
| 1101221 | CS130 | 100 | N | 1G-290 | CCW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101222 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101223 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101224 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101225 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101226 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 78 | 6500 | | |
| 1101227 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101228 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | | |
| 1101229 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101230 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101231 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101232 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101233 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101234 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101235 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101236 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101237 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101238 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101239 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101240 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | | |
| 1101241 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | | |
| 1101242 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | | |
| 1101243 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | | |
| 1101244 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.8 | 4.0-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | | |
| 1101245 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | | |
| 1101246 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101247 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101248 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101250 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | | |
| 1101251 | 27SI | 200 | N | 1G-270 | CW | 4558 | 2.4-2.8 | 4.2-5.0 | 12 | † | 22 | 1600 | 42 | 6500 | | |
| 1101252 | 17SI | 100 | N | 1G-266 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101253 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | | |
| 1101254 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | | |
| 1101255 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | | |
| 1101256 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101257 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101258 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | | |
| 1101436 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 | |
| 1101437 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 | |
| 1101438 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 | |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron
Generator
Model | Series | Type | Grd. | Service
Bulletin | Rotation
Viewing
D. E. | Spec.
No. | Field
Ohms
(80° F) | FIELD CURRENT
(80° F) | | Specified
Volts | COLD OUTPUT | | | | Rated
Hot
Output
(Amps) |
|---------------------------------|--------|------|------|---------------------|------------------------------|--------------|--------------------------|--------------------------|-------|--------------------|-------------|---------------|------|---------------|----------------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx
RPM | Amps | Approx
RPM | |
| 1101439 | 15SI | 116 | N | 1G-269 | EITHER | 4595 | 2.6-3.0 | 4.0-4.6 | 12 | † | 56 | 2000 | 100 | 5000 | 105 |
| 1101440 | 15SI | 116 | N | 1G-269 | EITHER | 7214 | 2.6-3.0 | 4.0-4.6 | 12 | † | 58 | 2000 | 115 | 7000 | 105 |
| 1101441 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101442 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101443 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101444 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101446 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101447 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101448 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1101449 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101450 | 27SI | 200 | N | 1G-266 | CW | 4525 | 2.6-3.0 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1101924 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1101925 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1102366 | 10SI | 102 | N | | EITHER | 4536 | 22-24 | 1.0-1.1 | 24 | 28 | 20 | 2000 | 29 | 5000 | 21 |
| 1102918 | 10SI | 116 | N | 1G-277 | EITHER | 4545 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1102919 | 10SI | 116 | N | 1G-277 | EITHER | 4563 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1102920 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1102921 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102922 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1102924 | 10SI | 116 | N | 1G-277 | EITHER | 4582 | 2.4-3.0 | 4.0-5.0 | 12 | † | 31 | 2600 | 39 | 7000 | 42 |
| 1102925 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1102926 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102927 | 10SI | 116 | N | 1G-269 | CW | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1102928 | 10SI | 116 | N | 1G-269 | CW | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102929 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102930 | 10SI | 116 | N | 1G-269 | CW | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1102931 | 10SI | 116 | N | 1G-277 | EITHER | 4553 | 2.4-3.0 | 4.0-5.0 | 12 | † | 40 | 2600 | 57 | 7000 | 61 |
| 1102932 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1102933 | 10SI | 136 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102934 | 10SI | 136 | N | 1G-277 | EITHER | 4545 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1102935 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1102936 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1102937 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1102938 | 10SI | 110 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1102939 | 10SI | 110 | N | 1G-267 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1102940 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1102941 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1102942 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2500 | 65 | 5000 | 72 |
| 1103033 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103034 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103035 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103036 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103037 | 10SI | 100 | N | 1G-266 | CW | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103039 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103040 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103041 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103042 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103043 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103044 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103045 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103046 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103047 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103048 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103049 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103050 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103051 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103052 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103053 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103054 | 10SI | 116 | N | 1G-269 | CW | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103055 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103056 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103057 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103058 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103059 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103060 | 10SI | 100 | N | 1G-266 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103061 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103062 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103063 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103064 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103065 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |

† At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D E | Spec. No. | Field Ohms (80° F) | FIELD CURRENT (80° F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|----------------------|-----------|--------------------|-----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1103066 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103067 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103068 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103069 | 10SI | 100 | N | 1G-266 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103070 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103071 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103072 | 10SI | 136 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103073 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103074 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103075 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103076 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103078 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103079 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103080 | 10SI | 100 | N | 1G-266 | CW | 4531 | 2.4-3.0 | 4.0-5.0 | 12 | † | 21 | 2000 | 31 | 5000 | 32 |
| 1103081 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103082 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103083 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103084 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103085 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103086 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103088 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103089 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103090 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103091 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103092 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103093 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103094 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103095 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103096 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103097 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103098 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103099 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103100 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103101 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103102 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103103 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103104 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103105 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103106 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103107 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103111 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103112 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103113 | 10SI | 110 | N | 1G-267 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103114 | 10SI | 110 | N | 1G-267 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103116 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103117 | 10SI | 100 | N | 1G-266 | EITHER | 7207 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 24 | 2000 | 36 | 7000 | 37 |
| 1103118 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103119 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103120 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103121 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103122 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103123 | 10SI | 116 | N | 1G-269 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1103124 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103125 | 10SI | 116 | N | 1G-269 | CW | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1103126 | 10SI | 116 | N | 1G-269 | CW | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103127 | 10SI | 116 | N | 1G-269 | CW | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103128 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103129 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103130 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103131 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1103132 | 10SI | 102 | N | 1G-267 | EITHER | 4536 | 22-24 | 1.0-1.1 | 24 | † | 20 | 2000 | 29 | 5000 | 21 |
| 1103133 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1103134 | 10SI | 102 | N | 1G-266 | EITHER | 4571 | 17-19 | 65-72 | 12 | † | 10 | 2000 | 18 | 5000 | 15 |
| 1103135 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103136 | 10SI | 116 | N | 1G-269 | EITHER | 4553 | 2.4-3.0 | 4.0-5.0 | 12 | † | 40 | 2600 | 57 | 7000 | 61 |
| 1103137 | 10SI | 116 | N | 1G-277 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103138 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1103139 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103140 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103141 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec No | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|------------------------|---------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1103142 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103143 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103144 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103145 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103146 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103147 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103148 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103149 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103151 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103152 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103153 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103154 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103155 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103156 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103157 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 51 | 5000 | 55 |
| 1103158 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103160 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 29 | 2000 | 75 | 7000 | 72 |
| 1103161 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103162 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103164 | 10SI | 116 | N | 1G-277 | CW | 4563 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1103165 | 10SI | 116 | N | 1G-277 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103166 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1103167 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 4.8-5.3 | 4.5-5.0 | 24 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103169 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103170 | 10SI | 100 | N | 1G-266 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103171 | 10SI | 116 | N | 1G-269 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103172 | 10SI | 116 | N | 1G-269 | EITHER | 7205 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 36 | 2000 | 63 | 7000 | 61 |
| 1103173 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 29 | 2000 | 75 | 7000 | 72 |
| 1103174 | 10SI | 116 | N | 1G-269 | EITHER | 7205 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 36 | 2000 | 63 | 7000 | 61 |
| 1103175 | 10SI | 116 | N | 1G-269 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103182 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103183 | 10SI | 116 | N | 1G-269 | EITHER | 7205 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 36 | 2000 | 63 | 7000 | 61 |
| 1103184 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 29 | 2000 | 75 | 7000 | 72 |
| 1103185 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1103186 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103187 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1103188 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 42 | 7000 | 42 |
| 1103189 | 10SI | 136 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1103190 | 10SI | 102 | N | 1G-266 | EITHER | 4544 | 22-24 | .50-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1103191 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1103192 | 10SI | 110 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103193 | 10SI | 110 | N | 1G-266 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1103194 | 10SI | 110 | N | 1G-266 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 20 | 2000 | 51 | 5000 | 55 |
| 1103195 | 10SI | 100 | N | 1G-266 | CW | 4520 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103196 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1103197 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105022 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-3.0 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105023 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-3.0 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105024 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-3.0 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105025 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105027 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105028 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105029 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105030 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105031 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105032 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105033 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105034 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105038 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105039 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105040 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105041 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105042 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105043 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105044 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105045 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105046 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105047 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105048 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105049 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |

† At maximum operating speed. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|-----------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1105050 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105058 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105059 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105060 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105061 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105062 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105063 | 10SI | 102 | N | 1G-266 | EITHER | 4544 | 22-24 | .5-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1105064 | 10SI | 110 | N | 1G-278 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105065 | 10SI | 110 | N | 1G-267 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105066 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1105067 | 10SI | 100 | N | 1G-266 | EITHER | 7207 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 24 | 2000 | 36 | 5000 | 37 |
| 1105068 | 10SI | 116 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1105069 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 36 | 5000 | 42 |
| 1105070 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 36 | 5000 | 42 |
| 1105071 | 10SI | 102 | N | 1G-266 | EITHER | 4571 | 15-20 | 6-8 | 12 | † | 10 | 2000 | 18 | 5000 | 15 |
| 1105072 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 36 | 5000 | 42 |
| 1105073 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105074 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 28 | 2000 | 36 | 5000 | 42 |
| 1105075 | 10SI | 136 | N | 1G-269 | EITHER | 4522 | 2.4-3.0 | 4.0-5.0 | 12 | † | 30 | 2000 | 57 | 5000 | 61 |
| 1105076 | 10SI | 102 | N | 1G-266 | EITHER | 4544 | 22-24 | .5-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1105077 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 4.8-5.3 | 4.5-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105078 | 10SI | 110 | N | 1G-267 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105079 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105080 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105081 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105082 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105083 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105084 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105085 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | 72 |
| 1105086 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105087 | 10SI | 102 | N | 1G-266 | EITHER | 4552 | 22-24 | 1.0-1.1 | 24 | † | 14 | 2500 | 20 | 7000 | 18 |
| 1105088 | 10SI | 110 | N | 1G-278 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105089 | 10SI | 110 | N | 1G-267 | EITHER | 4568 | 2.6-3.0 | 4.0-4.6 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105090 | 10DN | 100 | N | 1G-262B | EITHER | 3396 | 4.6-5.5 | 2.2-2.6 | 12 | † | 28 | 2000 | 37 | 5000 | 42 |
| 1105091 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105092 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105094 | 10SI | 102 | N | 1G-267 | EITHER | 4551 | 22-24 | .5-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1105095 | 10SI | 102 | N | 1G-266 | EITHER | 4544 | 22-24 | .5-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1105096 | 10SI | 102 | N | 1G-267 | EITHER | 4552 | 22-24 | 1.0-1.1 | 24 | † | 14 | 2500 | 20 | 7000 | 18 |
| 1105097 | 10SI | 110 | N | 1G-268 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105098 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105099 | 10SI | 136 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105100 | 10SI | 136 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105159 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105160 | 10SI | 116 | N | 1G-269 | CW | 7204 | 2.4-2.7 | 4.5-5.0 | 12 | † | 28 | 2000 | 42 | 7000 | 72 |
| 1105161 | 10SI | 116 | N | 1G-277 | EITHER | 4582 | 2.6-3.0 | 4.0-4.6 | 12 | † | 31 | 2600 | 39 | 7000 | 42 |
| 1105162 | 10SI | 116 | N | 1G-269 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105163 | 10SI | 116 | N | 1G-269 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105164 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105166 | 10SI | 116 | N | 1G-269 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105167 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105168 | 10SI | 116 | N | 1G-277 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105169 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105170 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105171 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105172 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-2.7 | 4.5-5.0 | 12 | † | 29 | 2000 | 75 | 7000 | 72 |
| 1105173 | 10SI | 116 | N | 1G-269 | CW | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105174 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105175 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105176 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-2.7 | 4.5-5.0 | 12 | † | 29 | 2000 | 75 | 7000 | 72 |
| 1105177 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-2.7 | 4.5-5.0 | 12 | † | 29 | 2000 | 75 | 7000 | 72 |
| 1105178 | 10SI | 116 | N | 1G-269 | EITHER | 7206 | 2.4-2.7 | 4.5-5.0 | 12 | † | 29 | 2000 | 75 | 7000 | 72 |
| 1105179 | 10SI | 116 | N | 1G-269 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105180 | 10SI | 116 | N | 1G-277 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105183 | 12SI | 100 | N | 1G-266 | EITHER | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105185 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105186 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105187 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105189 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105190 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |

† At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|------------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1105191 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105192 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105193 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105194 | 12SI | 100 | N | 1G-266 | CW | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105195 | 10SI | 110 | N | 1G-278 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105196 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105197 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105198 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105199 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105200 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105243 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105244 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105245 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105246 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105247 | 15SI | 100 | N | 1G-266 | CW | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105248 | 15SI | 100 | N | 1G-266 | CW | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105249 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105250 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105328 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105329 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105330 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105331 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105332 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105333 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105334 | 15SI | 100 | N | 1G-266 | EITHER | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105335 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105336 | 15SI | 100 | N | 1G-266 | EITHER | 4591 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105337 | 15SI | 100 | N | 1G-266 | EITHER | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105338 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105339 | 15SI | 100 | N | 1G-266 | EITHER | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105340 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105341 | 15SI | 100 | N | 1G-266 | EITHER | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105342 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105343 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105344 | 10SI | 100 | I | 1G-266 | CW | 7219 | 2.4-2.7 | 4.5-5.0 | 12 | † | 24 | 2000 | 36 | 7000 | 37 |
| 1105345 | 27SI | 100 | I | 1G-266 | CW | 7220 | 2.4-2.7 | 4.5-5.0 | 12 | † | 66 | 2000 | 103 | 7000 | 100 |
| 1105346 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105347 | 15SI | 100 | N | 1G-266 | EITHER | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105348 | 10SI | 100 | N | 1G-266 | CW | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105349 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105350 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105351 | 10SI | 100 | N | 1G-266 | EITHER | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105354 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105355 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105356 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105357 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105358 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105359 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105360 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105361 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105362 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105363 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105364 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105365 | 10SI | 100 | N | 1G-266 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105366 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 1105367 | 12SI | 100 | N | 1G-266 | EITHER | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105368 | 12SI | 100 | N | 1G-266 | EITHER | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105369 | 12SI | 100 | N | 1G-266 | EITHER | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105370 | 12SI | 100 | N | 1G-266 | EITHER | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105371 | 12SI | 100 | N | 1G-266 | EITHER | 7237 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105372 | 12SI | 100 | N | 1G-266 | EITHER | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105373 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 1105374 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105415 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1105416 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 1105418 | 15SI | 116 | N | 1G-269 | CW | 4595 | 2.6-3.0 | 4.0-4.6 | 12 | † | 56 | 2000 | 110 | 5000 | 105 |
| 1105419 | 10SI | 116 | N | 1G-269 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105420 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-2.7 | 4.5-5.0 | 12 | † | 28 | 2000 | 42 | 7000 | 42 |
| 1105421 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105422 | 10SI | 116 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron
Generator
Model | Series | Type | Grd. | Service
Bulletin | Rotation
Viewing
D E | Spec.
No. | Field
Ohms
(80°F) | FIELD CURRENT
(80°F) | | Specified
Volts | COLD OUTPUT | | | | Rated
Hot
Output
(Amps) |
|---------------------------------|--------|------|------|---------------------|----------------------------|--------------|-------------------------|-------------------------|-------|--------------------|-------------|----------------|------|----------------|----------------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx.
RPM | Amps | Approx.
RPM | |
| 1105423 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105424 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-2.7 | 4.5-5.0 | 12 | † | 28 | 2000 | 42 | 7000 | 42 |
| 1105425 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105426 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105427 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105428 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 63 | 2000 | 103 | 7000 | 94 |
| 1105429 | 10SI | 116 | N | 1G-269 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105430 | 10SI | 136 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105431 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105432 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105433 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105434 | 10SI | 116 | N | 1G-277 | EITHER | 4582 | 2.6-3.0 | 4.0-4.6 | 12 | † | 31 | 2600 | 39 | 7000 | 42 |
| 1105435 | 10SI | 136 | N | 1G-269 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105436 | 10SI | 136 | N | 1G-269 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105437 | 10SI | 116 | N | 1G-277 | EITHER | 4545 | 4.8-6.0 | 4.0-5.0 | 24 | † | 25 | 2600 | 41 | 7000 | 40 |
| 1105438 | 15SI | 100 | N | 1G-266 | EITHER | 7215 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105439 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105440 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105441 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105442 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105443 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105444 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105445 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105446 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105447 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105448 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105449 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105450 | 17SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105451 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105453 | 10SI | 102 | N | 1G-267 | EITHER | 4552 | 22-24 | 1.0-1.1 | 24 | † | 14 | 2500 | 20 | 7000 | 18 |
| 1105454 | 10SI | 102 | N | 1G-267 | EITHER | 4552 | 22-24 | 1.0-1.1 | 24 | † | 14 | 2500 | 20 | 7000 | 18 |
| 1105455 | 10SI | 116 | N | 1G-277 | EITHER | 4582 | 2.6-3.0 | 4.0-4.6 | 12 | † | 31 | 2600 | 39 | 7000 | 42 |
| 1105456 | 10SI | 116 | N | 1G-277 | EITHER | 4582 | 2.6-3.0 | 4.0-4.6 | 12 | † | 31 | 2600 | 39 | 7000 | 42 |
| 1105457 | 10SI | 116 | N | 1G-277 | EITHER | 4533 | 2.4-3.0 | 4.0-5.0 | 12 | † | 32 | 2000 | 60 | 5000 | 63 |
| 1105458 | 10SI | 116 | N | 1G-277 | EITHER | 4563 | 4.8-6.0 | 4.0-5.0 | 24 | † | 26 | 2600 | 43 | 7000 | 40 |
| 1105459 | 10SI | 116 | N | 1G-277 | EITHER | 4563 | 4.8-6.0 | 4.0-5.0 | 24 | † | 26 | 2600 | 43 | 7000 | 40 |
| 1105460 | 27SI | 200 | N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1105461 | 27SI | 200 | P | 1G-270 | CW | 4560 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1105463 | 27SI | 200 | N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1105464 | 27SI | 200 | N | 1G-270 | EITHER | 4559 | 2.4-2.7 | 4.4-4.9 | 12 | † | 46 | 2000 | 58 | 5000 | 65 |
| 1105465 | 27SI | 200 | N | 1G-270 | CW | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1105466 | 27SI | 200 | P | 1G-270 | CW | 4561 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1105469 | 27SI | 200 | N | 1G-270 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1105470 | 27SI | 200 | N | 1G-270 | EITHER | 4558 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1105471 | 27SI | 200 | P | 1G-270 | EITHER | 4561 | 2.4-2.7 | 4.4-4.9 | 12 | † | 52 | 2000 | 72 | 5000 | 80 |
| 1105472 | 27SI | 200 | N | 1G-270 | CW | 4593 | 2.2-2.7 | 4.5-5.5 | 12 | † | 73 | 2850 | 83 | 7000 | 100 |
| 1105473 | 27SI | 200 | N | 1G-270 | EITHER | 4593 | 2.2-2.7 | 4.5-5.5 | 12 | † | 73 | 2850 | 83 | 7000 | 100 |
| 1105474 | 27SI | 200 | N | 1G-270 | CW | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1105475 | 27SI | 200 | N | 1G-270 | EITHER | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1105476 | 27SI | 200 | N | 1G-270 | EITHER | 4547 | 11-12 | 2.1-2.2 | 24 | † | 25 | 2000 | 60 | 5000 | 65 |
| 1105477 | 27SI | 202 | N | 1G-270 | EITHER | 4548 | 24-40 | 0.6-1.0 | 24 | † | 20 | 2000 | 32 | 5000 | 30 |
| 1105478 | 10SI | 110 | N | 1G-267 | EITHER | 4568 | 2.6-3.0 | 4.0-4.6 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105479 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 108 |
| 1105480 | 12SI | 100 | N | 1G-266 | CW | 7236 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 94 |
| 1105481 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 108 |
| 1105482 | 10SI | 102 | N | 1G-267 | EITHER | 4551 | 22-24 | .5-.55 | 12 | † | 10 | 2000 | 20 | 5000 | 18 |
| 1105491 | 17SI | 100 | N | 1G-266 | EITHER | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105492 | 12SI | 100 | N | 1G-266 | EITHER | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105493 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105494 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105495 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105496 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105497 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 108 |
| 1105499 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105500 | 27SI | 100 | I | 1G-266 | CW | 7220 | 2.4-2.8 | 4.2-5.0 | 12 | † | 44 | 1600 | 100 | 6500 | |
| 1105503 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105504 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105505 | 10SI | 100 | N | 1G-266 | EITHER | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105506 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105507 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|------------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1105594 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105595 | 17SI | 100 | N | 1G-266 | CW | 7238 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 105 | 7000 | 97 |
| 1105596 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105597 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105598 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105599 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105600 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105601 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105602 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105603 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105604 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105606 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105607 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-2.7 | 4.5-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105608 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-2.7 | 4.5-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105609 | 15SI | 116 | N | 1G-269 | EITHER | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1105610 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105611 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105612 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 120 |
| 1105613 | 27SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105614 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | 120 |
| 1105615 | CS144 | 100 | N | 1G-291 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | 108 |
| 1105616 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | 108 |
| 1105617 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | 72 |
| 1105618 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 72 |
| 1105619 | 10SI | 116 | N | 1G-269 | EITHER | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105620 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105621 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105622 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 7000 | 85 |
| 1105623 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105624 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105625 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | 108 |
| 1105626 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | 108 |
| 1105627 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105628 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105629 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105630 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105631 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105632 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105633 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105634 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105635 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105636 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105637 | 27SI | 100 | N | 1G-266 | CW | 4574 | 2.4-2.7 | 4.4-4.9 | 12 | † | 63 | 2000 | 97 | 5000 | 100 |
| 1105638 | CS121 | 100 | N | 1G-290 | CW | 7264 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | 108 |
| 1105639 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 108 |
| 1105641 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 42 |
| 1105644 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 42 |
| 1105645 | 10SI | 116 | N | 1G-269 | EITHER | 7204 | 2.4-2.7 | 4.5-5.0 | 12 | † | 28 | 2000 | 42 | 7000 | 42 |
| 1105646 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 42 |
| 1105647 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105648 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105649 | 10SI | 100 | N | 1G-266 | EITHER | 7207 | 2.4-3.0 | 4.0-5.0 | 12 | 14 | 24 | 2000 | 36 | 500 | 37 |
| 1105650 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105651 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105652 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105653 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105654 | 12SI | 100 | N | 1G-266 | CW | 7235 | 2.4-2.7 | 4.5-5.0 | 12 | † | 56 | 2000 | 103 | 7000 | 94 |
| 1105655 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105656 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105657 | CS144 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | 120 |
| 1105658 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105659 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | 120 |
| 1105660 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | 120 |
| 1105661 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | 120 |
| 1105662 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 120 |
| 1105663 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 120 |
| 1105664 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 120 |
| 1105665 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 120 |
| 1105666 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | 120 |
| 1105667 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | 120 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd. | Service Bulletin | Rotation Viewing D E | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|------|------------------|----------------------|----------|-------------------|----------------------|-------|-----------------|-------------|-------------|------|-------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx. RPM | Amps | Approx. RPM | |
| 1105668 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105669 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105670 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105671 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105672 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105673 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105674 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105675 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105676 | 12SI | 100 | N | 1G-266 | CW | 7211 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 60 | 7000 | 56 |
| 1105677 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-2.7 | 4.5-5.0 | 12 | † | 25 | 2000 | 38 | 5000 | 42 |
| 1105678 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105680 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105681 | 17SI | 100 | N | 1G-266 | CW | 7240 | 2.6-3.0 | 4.0-4.6 | 12 | † | 75 | 2000 | 115 | 7000 | 108 |
| 1105683 | 17SI | 100 | N | 1G-266 | CW | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105684 | CS144 | 100 | N | 1G-291 | CW | 7255 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 1105685 | CS440 | 100 | N | 1G-291 | CW | 7246 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 1105686 | 10SI | 116 | N | 1G-269 | CW | 7242 | 2.4-2.7 | 4.4-4.9 | 12 | † | 40 | 2600 | 60 | 7000 | 63 |
| 1105688 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105689 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105690 | 17SI | 100 | N | 1G-266 | EITHER | 7243 | 1.7-2.2 | 5.5-7.0 | 12 | † | 54 | 1600 | 130 | 6500 | 120 |
| 1105691 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-2.7 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105692 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105693 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1105694 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105695 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105696 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105697 | CS121 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1105698 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105700 | 17SI | 100 | N | 1G-266 | CW | 7216 | 2.4-2.7 | 4.5-5.0 | 12 | † | 75 | 2000 | 115 | 7000 | 97 |
| 1105701 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105702 | 10SI | 136 | N | 1G-269 | CW | 4537 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 65 | 5000 | 72 |
| 1105703 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105704 | 10SI | 100 | N | 1G-266 | CW | 4519 | 2.4-3.0 | 4.0-5.0 | 12 | † | 22 | 2000 | 33 | 5000 | 37 |
| 1105705 | 10SI | 100 | N | 1G-266 | CW | 4521 | 2.4-3.0 | 4.0-5.0 | 12 | † | 25 | 2000 | 3800 | 5000 | 42 |
| 1105706 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105707 | 12SI | 100 | N | 1G-266 | CW | 7212 | 2.4-2.7 | 4.5-5.0 | 12 | † | 38 | 2000 | 70 | 7000 | 66 |
| 1105708 | 12SI | 100 | N | 1G-266 | CW | 7210 | 2.4-2.7 | 4.5-5.0 | 12 | † | 51 | 2000 | 81 | 7000 | 78 |
| 1105709 | 27SI | 100 | N | 1G-266 | CW | 4525 | 2.4-2.7 | 4.4-4.9 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 1105710 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105711 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105712 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105713 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105714 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105715 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105716 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105717 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105718 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105719 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105720 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1105721 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105722 | CS130 | 100 | N | 1G-290 | CW | 7254 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 1105723 | CS130 | 100 | N | 1G-290 | CW | 7249 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 1105724 | CS130 | 100 | N | 1G-290 | CW | 7248 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 1105725 | CS130 | 100 | N | 1G-290 | CW | 7245 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 1117067 | 30SI | 400 | N | 1G-280 | EITHER | 4567 | 2.7-3.4 | 3.6-4.3 | 12 | † | 68 | 2500 | 86 | 6500 | 90 |
| 1117068 | 30SI | 400 | N | 1G-280 | EITHER | 4567 | 2.7-3.4 | 3.6-4.3 | 12 | † | 68 | 2500 | 86 | 6500 | 90 |
| 1117069 | 25SI | 450 | N | 1G-275 | EITHER | 4539 | 8.5-9.6 | 2.5-2.8 | 24 | † | | | 70 | 5000 | 75 |
| 1117160 | 29SI | 300 | N | 1G-276 | EITHER | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117161 | 29SI | 300 | N | 1G-276 | CW | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117162 | 29SI | 300 | N | 1G-276 | EITHER | 4567 | 2.4-2.9 | 4.2-5.0 | 12 | 13 | 4 | 2500 | 84 | 6500 | 90 |
| 1117163 | 29SI | 300 | N | 1G-276 | EITHER | 4565 | 8.5-9.5 | 2.5-2.8 | 24 | 26 | 46 | 2600 | 60 | 6500 | 60 |
| 1117164 | 29SI | 300 | N | 1G-276 | EITHER | 4599 | 2.4-2.9 | 4.2-5.0 | 12 | † | 75 | 2700 | 94 | 8000 | 90 |
| 1117165 | 29SI | 300 | N | 1G-276 | CW | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117170 | 31SI | 500 | N | 1G-282 | EITHER | 4579 | 1.5-2.0 | 6.1-7.8 | 12 | 13 | 45 | 2500 | 140 | 6500 | 135 |
| 1117171 | 31SI | 500 | I | 1G-282 | EITHER | 4583 | 4.3-4.7 | 5.1-5.6 | 24 | 26 | 30 | 2500 | 75 | 6500 | 75 |
| 1117172 | 31SI | 500 | N | 1G-282 | EITHER | 7209 | 1.5-2.0 | 6.1-7.8 | 12 | † | 54 | 2500 | 83 | 6500 | 85 |
| 1117173 | 31SI | 550 | N | 1G-282 | EITHER | 4583 | 4.3-4.7 | 5.1-5.6 | 24 | 26 | 30 | 2500 | 75 | 6500 | 75 |
| 1117180 | 32SI | 600 | N | 1G-282 | EITHER | 4580 | 1.5-2.0 | 6.1-7.8 | 12 | 13 | 54 | 2500 | 82 | 6500 | 85 |
| 1117181 | 32SI | 600 | N | 1G-282 | EITHER | 4587 | 8.6-9.6 | 2.5-2.8 | 24 | 26 | 27 | 2500 | 50 | 6500 | 50 |
| 1117182 | 32SI | 600 | N | 1G-282 | EITHER | 4589 | 1.5-2.0 | 6.1-7.8 | 12 | 13 | 54 | 2500 | 85 | 6500 | 85 |

† At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E | Spec No | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|-----------------------|---------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1117183 | 32SI | 600 | N | 1G-282 | EITHER | 4580 | 1.5-2.0 | 6.1-7.8 | 12 | 13 | 54 | 2500 | 82 | 6500 | 85 |
| 1117184 | 32SI | 600 | I | 1G-282 | EITHER | 7208 | 8.6-9.6 | 2.5-2.8 | 24 | † | 13 | 2500 | 85 | 6500 | 85 |
| 1117185 | 32SI | 600 | N | 1G-282 | EITHER | 4580 | 1.5-2.0 | 6.1-7.8 | 12 | 13 | 54 | 2500 | 82 | 6500 | 85 |
| 1117251 | 25SI | 400 | N | 1G-275 | EITHER | 4596 | 2.4-2.8 | 4.3-5.0 | 12 | † | 66 | 2700 | 76 | 8000 | 75 |
| 1117252 | 25SI | 400 | P | 1G-275 | EITHER | 4596 | 2.4-2.8 | 4.3-5.0 | 12 | † | 66 | 2700 | 76 | 8000 | 75 |
| 1117253 | 25SI | 440 | N | 1G-275 | EITHER | 4597 | 8.6-9.6 | 2.5-2.8 | 24 | 27 | 43 | 2700 | 52 | 8000 | 50 |
| 1117254 | 25SI | 450 | N | 1G-275 | EITHER | 7203 | 8.6-9.6 | 2.5-2.8 | 24 | † | 27 | 2600 | 50 | 6500 | 50 |
| 1117255 | 25SI | 450 | N | 1G-275 | EITHER | 4598 | 2.4-2.8 | 4.3-5.0 | 12 | † | 66 | 2700 | 76 | 8000 | 75 |
| 1117256 | 25SI | 450 | N | 1G-275 | EITHER | 4539 | 8.6-9.6 | 2.5-2.8 | 24 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1117258 | 25SI | 450 | N | 1G-275 | EITHER | 4597 | 8.6-9.6 | 2.5-2.8 | 24 | 27 | 43 | 2700 | 52 | 8000 | 50 |
| 1117259 | 25SI | 450 | N | 1G-275 | EITHER | 4598 | 2.4-2.8 | 4.3-5.0 | 12 | † | 66 | 2700 | 76 | 8000 | 75 |
| 1117260 | 25SI | 450 | N | 1G-275 | EITHER | 4515 | 2.7-2.9 | 4.1-4.5 | 12 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1117261 | 25SI | 400 | N | 1G-275 | CW | 4507 | 2.7-2.9 | 4.1-4.5 | 12 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1117262 | 25SI | 450 | N | 1G-275 | CW | 4515 | 2.7-2.9 | 4.1-4.5 | 12 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1117263 | 25SI | 450 | N | 1G-275 | EITHER | 4515 | 2.6-3.0 | 4.1-4.5 | 12 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1117485 | 30SI | 400 | N | 1G-280 | CW | 4567 | 2.7-3.4 | 3.6-4.3 | 12 | 13 | 68 | 2500 | 86 | 6500 | 90 |
| 1117611 | 20SI | 300 | N | 1G-276 | EITHER | 4577 | 1.7-2.1 | 5.7-7.1 | 12 | 14 | 28 | 2600 | 62 | 6500 | 60 |
| 1117612 | 20SI | 300 | N | 1G-276 | EITHER | 4577 | 1.7-2.1 | 5.7-7.1 | 12 | 14 | 28 | 2600 | 62 | 6500 | 60 |
| 1117613 | 20SI | 300 | N | 1G-276 | EITHER | 4577 | 1.7-2.1 | 5.7-7.1 | 12 | 14 | 28 | 2600 | 62 | 6500 | 60 |
| 1117614 | 20SI | 300 | N | 1G-276 | EITHER | 4578 | 6.0-7.3 | 3.3-3.8 | 24 | 26 | 12 | 2500 | 45 | 6500 | 45 |
| 1117615 | 20SI | 300 | N | 1G-276 | EITHER | 4578 | 6.0-7.3 | 3.3-3.8 | 24 | 26 | 12 | 2500 | 45 | 6500 | 45 |
| 1117616 | 20SI | 300 | N | 1G-276 | EITHER | 4577 | 1.6-2.2 | 5.7-7.1 | 12 | 14 | 28 | 2600 | 62 | 6500 | 60 |
| 1117640 | 20SI | 300 | N | 1G-276 | EITHER | 4576 | 6.3-7.3 | 3.3-3.8 | 24 | 28 | 15 | 2600 | 34 | 6500 | 35 |
| 1117641 | 20SI | 300 | N | 1G-276 | EITHER | 4577 | 1.7-2.1 | 5.7-7.1 | 12 | 14 | 28 | 2600 | 62 | 6500 | 60 |
| 1117642 | 20SI | 300 | N | 1G-276 | EITHER | 4578 | 6.3-7.3 | 3.3-3.8 | 24 | 26 | 12 | 2500 | 45 | 6500 | 45 |
| 1117643 | 20SI | 300 | N | 1G-276 | EITHER | 4588 | 6.3-7.3 | 3.3-3.8 | 24 | 26 | 12 | 2500 | 45 | 6500 | 45 |
| 1117644 | 20SI | 300 | N | 1G-276 | EITHER | 4576 | 6.3-7.3 | 3.3-3.8 | 24 | 28 | 15 | 2600 | 34 | 6500 | 35 |
| 1117645 | 20SI | 300 | N | 1G-276 | EITHER | 4588 | 6.3-7.3 | 3.3-3.8 | 24 | 26 | 12 | 2500 | 45 | 6500 | 45 |
| 1117647 | 20SI | 300 | N | 1G-276 | EITHER | 4576 | 6.3-7.3 | 3.3-3.8 | 24 | † | 15 | 2500 | 34 | 6500 | 35 |
| 1117648 | 30SI | 450 | I | 1G-280 | EITHER | 7201 | 8.6-9.6 | 2.5-2.8 | 24 | † | 45 | 2700 | 59 | 8000 | 60 |
| 1117649 | 30SI | 450 | I | 1G-280 | EITHER | 7202 | 18-22 | 1.5-1.7 | 32 | † | 36 | 2700 | 61 | 8000 | 60 |
| 1117650 | 20SI | 300 | N | 1G-276 | EITHER | 4576 | 6.3-7.3 | 3.3-3.8 | 24 | † | 15 | 2500 | 34 | 6500 | 35 |
| 1117655 | 20SI | 300 | N | 1G-276 | EITHER | 4576 | 6.3-7.3 | 3.3-3.8 | 24 | † | 15 | 2500 | 34 | 6500 | 35 |
| 1117701 | 50DN | 600 | N | 1G-254 | EITHER | 3386 | 1.4-1.5 | 8.1-8.4 | 12 | 14 | 80 | 1000 | 215 | 1500 | 300 |
| 1117702 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165 | 1800 | 250 | 3000 | 270 |
| 1117703 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165 | 1800 | 250 | 3000 | 270 |
| 1117704 | 50DN | 600 | N | 1G-254 | EITHER | 3386 | 1.4-1.5 | 8.1-8.4 | 12 | 14 | 80 | 1000 | 215 | 1500 | 300 |
| 1117705 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165 | 1800 | 250 | 3000 | 270 |
| 1117734 | 30SI | 450 | I | 1G-280 | EITHER | 4565 | 8.5-9.5 | 2.5-2.8 | 24 | 26 | 46 | 2600 | 60 | 6500 | 60 |
| 1117740 | 50DN | 600 | N | 1G-254 | EITHER | 4573 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 130* | 1800 | 280* | 3000 | 350 |
| 1117741 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 170* | 1800 | 250* | 3000 | 270 |
| 1117742 | 30SI | 400 | N | 1G-280 | EITHER | 4599 | 2.4-2.9 | 4.2-5.0 | 12 | † | 75 | 2700 | 94 | 8000 | 90 |
| 1117743 | 30SI | 400 | P | 1G-280 | EITHER | 4599 | 2.4-2.9 | 4.2-5.0 | 12 | † | 75 | 2700 | 94 | 8000 | 90 |
| 1117744 | 30SI | 400 | N | 1G-280 | EITHER | 7200 | 2.4-2.9 | 4.2-5.0 | 12 | † | 70 | 2700 | 91 | 8000 | 90 |
| 1117745 | 30SI | 400 | P | 1G-280 | EITHER | 7200 | 2.4-2.9 | 4.2-5.0 | 12 | † | 70 | 2700 | 91 | 8000 | 90 |
| 1117746 | 30SI | 450 | N | 1G-280 | EITHER | 7201 | 8.6-9.6 | 2.5-2.8 | 24 | † | 45 | 2700 | 59 | 8000 | 60 |
| 1117747 | 30SI | 450 | N | 1G-280 | EITHER | 7202 | 18-22 | 1.5-1.7 | 32 | † | 36 | 2700 | 61 | 8000 | 60 |
| 1117748 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117749 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117789 | 50DN | 600 | N | 1G-254 | EITHER | 3386 | 1.4-1.5 | 8.1-8.5 | 12 | 14 | 80* | 1000 | 215* | 1500 | 300 |
| 1117790 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117791 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117792 | 50DN | 600 | N | 1G-254 | EITHER | 4555 | 3.8-4.2 | 5.7-6.2 | 24 | 28 | 80* | 1200 | 225* | 2500 | 240 |
| 1117793 | 50DN | 600 | N | 1G-254 | EITHER | 3386 | 1.4-1.5 | 8.1-8.4 | 12 | 14 | 80* | 1000 | 215* | 1500 | 300 |
| 1117794 | 50DN | 600 | N | 1G-254 | EITHER | 4555 | 3.8-4.2 | 5.7-6.2 | 24 | 28 | 80* | 1200 | 225* | 2500 | 240 |
| 1117795 | 50DN | 600 | N | 1G-254 | EITHER | 4573 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 130* | 1800 | 280* | 3000 | 350 |
| 1117796 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117797 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117798 | 50DN | 600 | N | 1G-254 | EITHER | 3386 | 1.4-1.5 | 8.1-8.4 | 12 | 14 | 80* | 1000 | 215* | 1500 | 300 |
| 1117799 | 50DN | 600 | N | 1G-254 | EITHER | 4581 | 3.0-3.4 | 7.2-8.0 | 24 | 28 | 165* | 1800 | 250* | 3000 | 270 |
| 1117800 | 30SI | 400 | N | 1G-280 | CW | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117801 | 30SI | 400 | N | 1G-281 | EITHER | 7271 | 2.4-2.8 | 4.2-5.0 | 12 | † | 95 | 2600 | 115 | 6500 | 105 |
| 1117802 | 30SI | 400 | P | 1G-281 | EITHER | 7271 | 2.4-2.8 | 4.2-5.0 | 12 | † | 95 | 2600 | 115 | 6500 | 105 |
| 1117803 | 30SI | 400 | N | 1G-281 | EITHER | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117804 | 30SI | 400 | N | 1G-281 | EITHER | 4564 | 2.4-2.9 | 4.2-5.0 | 12 | 14 | 60 | 2600 | 88 | 6500 | 90 |
| 1117805 | 30SI | 400 | N | 1G-281 | EITHER | 7272 | 8.6-9.4 | 2.5-2.8 | 24 | † | 70 | 5000 | 75 | 5000 | 75 |
| 1972711 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1972723 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1972724 | 27SI | 100 | N | 1G-266 | CW | 7225 | 2.2-2.7 | 4.5-5.5 | 12 | † | 63 | 2000 | 98 | 7000 | 100 |
| 1979857 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 23 | 2000 | 34 | 7000 | 37 |

‡ At maximum operating speed.
 † Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.
 * If the generator output is checked without a regulator, the output should be 5-10% higher than the value given.
 I Insulated.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D E | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|----------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 1979858 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1979859 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1979860 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1979861 | 10SI | 100 | N | 1G-266 | CW | 7223 | 2.4-2.7 | 4.5-5.0 | 12 | † | 32 | 2000 | 52 | 7000 | 55 |
| 1979862 | 10SI | 100 | N | 1G-266 | CW | 7223 | 2.4-2.7 | 4.5-5.0 | 12 | † | 32 | 2000 | 52 | 7000 | 55 |
| 1979863 | 10SI | 100 | N | 1G-266 | CW | 7223 | 2.4-2.7 | 4.5-5.0 | 12 | † | 32 | 2000 | 52 | 7000 | 55 |
| 1979864 | 10SI | 100 | N | 1G-266 | CW | 7223 | 2.4-2.7 | 4.5-5.0 | 12 | † | 32 | 2000 | 52 | 7000 | 55 |
| 1979865 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1979866 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1979867 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1979868 | 27SI | 100 | N | 1G-266 | CW | 7225 | 2.2-2.7 | 4.5-5.5 | 12 | † | 58 | 2000 | 80 | 7000 | 80 |
| 1979871 | 10SI | 116 | N | 1G-269 | EITHER | 7233 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1979872 | 10SI | 116 | N | 1G-269 | EITHER | 7224 | 2.4-2.7 | 4.5-5.0 | 12 | † | 34 | 2000 | 60 | 7000 | 61 |
| 1979873 | 10SI | 116 | N | 1G-269 | EITHER | 7227 | 2.6-3.0 | 4.0-4.6 | 12 | † | 28 | 2000 | 71 | 7000 | 72 |
| 1979874 | 10SI | 116 | N | 1G-269 | EITHER | 7224 | 2.4-2.7 | 4.5-5.0 | 12 | † | 34 | 2000 | 60 | 7000 | 61 |
| 1979875 | 10SI | 116 | N | 1G-269 | EITHER | 7228 | 2.6-3.0 | 4.0-4.6 | 12 | † | 25 | 2000 | 41 | 7000 | 40 |
| 1984269 | 15SI | 100 | N | 1G-266 | CW | 7234 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 72 | 7000 | 70 |
| 1984270 | 15SI | 100 | N | 1G-266 | CW | 7234 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 72 | 7000 | 70 |
| 1984271 | 15SI | 100 | N | 1G-266 | CW | 7234 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 72 | 7000 | 70 |
| 1984272 | 15SI | 100 | N | 1G-266 | CW | 7234 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 72 | 7000 | 70 |
| 1984277 | 27SI | 200 | N | 1G-270 | EITHER | 7229 | 11-12 | 2.1-2.2 | 24 | † | 42 | 2800 | 60 | 7000 | 65 |
| 1984278 | 10SI | 116 | N | 1G-277 | EITHER | 7230 | 2.6-3.0 | 4.0-4.6 | 12 | † | 37 | 2600 | 51 | 7000 | 61 |
| 1984279 | 10SI | 136 | N | 1G-269 | EITHER | 7227 | 2.6-3.0 | 4.0-4.6 | 12 | † | 28 | 2000 | 71 | 7000 | 72 |
| 1984280 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1984281 | 10SI | 100 | N | 1G-266 | EITHER | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 1984282 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 1985153 | 10SI | 136 | N | 1G-269 | EITHER | 7224 | 2.4-2.7 | 4.5-5.0 | 12 | † | 34 | 2000 | 60 | 7000 | 61 |
| 1985154 | 10SI | 136 | N | 1G-269 | EITHER | 7228 | 2.6-3.0 | 4.0-4.6 | 12 | † | 25 | 2000 | 41 | 7000 | 40 |
| 1985155 | 27SI | 200 | N | 1G-270 | EITHER | 7232 | 2.2-2.7 | 4.5-5.5 | 12 | † | 44 | 2500 | 53 | 7000 | 65 |
| 1985874 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 1985875 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1985876 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 1985877 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 10456300 | CS121 | 100 | N | 1G-290 | CW | 7273 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456301 | CS121 | 100 | N | 1G-290 | CW | 7274 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456302 | CS121 | 100 | N | 1G-290 | CW | 7273 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456303 | CS121 | 100 | N | 1G-290 | CW | 7274 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456304 | CS121 | 100 | N | 1G-290 | CW | 7274 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456305 | CS121 | 100 | N | 1G-290 | CW | 7273 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456306 | CS121 | 100 | N | 1G-290 | CW | 7273 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456307 | CS121 | 100 | N | 1G-290 | CW | 7274 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456308 | CS121 | 100 | N | 1G-290 | CW | 7275 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456309 | CS121 | 100 | N | 1G-290 | CW | 7276 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456310 | CS121 | 100 | N | 1G-290 | CW | 7275 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456311 | CS121 | 100 | N | 1G-290 | CW | 7276 | 2.3-2.6 | 4.6-5.3 | 12 | † | 26 | 1600 | 61 | 6500 | |
| 10456312 | CS121 | 100 | N | 1G-290 | CW | 7274 | 1.8-2.0 | 6.0-6.7 | 12 | † | 28 | 1600 | 74 | 6500 | |
| 10456313 | 27SI | 200 | N | 1G-266 | CW | 4525 | 2.4-2.8 | 4.2-5.0 | 12 | † | 55 | 2000 | 76 | 5000 | 80 |
| 10495382 | 10SI | 100 | N | 1G-266 | CW | 7226 | 2.4-2.7 | 4.5-5.0 | 12 | † | 37 | 2000 | 63 | 7000 | 63 |
| 10495383 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 10495384 | 10SI | 100 | N | 1G-266 | CW | 7222 | 2.4-2.7 | 4.5-5.0 | 12 | † | 27 | 2000 | 40 | 7000 | 42 |
| 10495385 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 10495386 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 10495387 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 10495388 | 15SI | 100 | N | 1G-266 | CW | 4586 | 2.6-3.0 | 4.0-4.6 | 12 | † | 57 | 2000 | 85 | 5000 | 85 |
| 10495389 | 15SI | 100 | N | 1G-266 | CW | 4584 | 2.6-3.0 | 4.0-4.6 | 12 | † | 55 | 2000 | 70 | 5000 | 70 |
| 10495418 | 15SI | 100 | N | 1G-266 | CW | 7250 | 2.4-3.0 | 4.0-5.0 | 12 | † | 35 | 2000 | 57 | 7000 | 56 |
| 10495419 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495420 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-3.0 | 4.0-5.0 | 12 | † | 36 | 2000 | 67 | 7000 | 66 |
| 10495421 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-3.0 | 4.0-5.0 | 12 | † | 36 | 2000 | 67 | 7000 | 66 |
| 10495422 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495423 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-3.0 | 4.0-5.0 | 12 | † | 36 | 2000 | 67 | 7000 | 66 |
| 10495424 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495425 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495426 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495427 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495428 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495429 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495430 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495431 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10495432 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.

GENERATORS

| Delcotron Generator Model | Series | Type | Grd | Service Bulletin | Rotation Viewing D. E. | Spec No. | Field Ohms (80°F) | FIELD CURRENT (80°F) | | Specified Volts | COLD OUTPUT | | | | Rated Hot Output (Amps) |
|---------------------------|--------|------|-----|------------------|------------------------|----------|-------------------|----------------------|-------|-----------------|-------------|------------|------|------------|-------------------------|
| | | | | | | | | Amps | Volts | | Amps | Approx RPM | Amps | Approx RPM | |
| 10495433 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-3.0 | 4.0-5.0 | 12 | † | 36 | 2000 | 67 | 7000 | 66 |
| 10495434 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-3.0 | 4.0-5.0 | 12 | † | 36 | 2000 | 67 | 7000 | 66 |
| 10495435 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-3.0 | 4.0-5.0 | 12 | † | 48 | 2000 | 77 | 7000 | 78 |
| 10497074 | 12SI | 100 | N | 1G-266 | CW | 7250 | 2.4-2.8 | 4.2-5.0 | 12 | † | 25 | 1600 | 56 | 6500 | |
| 10497075 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | |
| 10497076 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | |
| 10497077 | 12SI | 100 | N | 1G-266 | CW | 7251 | 2.4-2.8 | 4.2-5.0 | 12 | † | 23 | 1600 | 66 | 6500 | |
| 10497078 | 12SI | 100 | N | 1G-266 | CW | 7252 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 78 | 6500 | |
| 10497079 | 12SI | 100 | N | 1G-266 | CW | 7260 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | |
| 10497080 | 12SI | 100 | N | 1G-266 | CW | 7260 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | |
| 10497081 | 12SI | 100 | N | 1G-266 | CW | 7260 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | |
| 10497082 | 12SI | 100 | N | 1G-266 | CW | 7260 | 2.4-2.8 | 4.2-5.0 | 12 | † | 30 | 1600 | 94 | 6500 | |
| 10497083 | 15SI | 116 | N | 1G-266 | CW | 7261 | 2.6-3.0 | 4.0-4.7 | 12 | † | 56 | 2000 | 110 | 5000 | 105 |
| 10497106 | CS130 | 100 | N | 1G-290 | CW | 7267 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 10497107 | CS144 | 100 | N | 1G-291 | CW | 7269 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 10497108 | CS144 | 100 | N | 1G-291 | CW | 7270 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 10497109 | CS144 | 100 | N | 1G-291 | CW | 7269 | 2.4-2.8 | 4.2-5.0 | 12 | † | 45 | 1600 | 108 | 6500 | |
| 10497110 | CS144 | 100 | N | 1G-291 | CW | 7270 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 10497111 | CS144 | 100 | N | 1G-291 | CW | 7270 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |
| 10497112 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497113 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497114 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497115 | CS130 | 100 | N | 1G-290 | CW | 7267 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 10497116 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497117 | CS130 | 100 | N | 1G-290 | CW | 7267 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 10497118 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497119 | CS130 | 100 | N | 1G-290 | CW | 7267 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 10497120 | CS130 | 100 | N | 1G-290 | CW | 7266 | 2.1-2.5 | 4.8-5.7 | 12 | † | 30 | 1600 | 85 | 6500 | |
| 10497121 | CS130 | 100 | N | 1G-290 | CW | 7267 | 1.6-2.0 | 6.0-7.5 | 12 | † | 36 | 1600 | 100 | 6500 | |
| 10497122 | CS130 | 100 | N | 1G-290 | CW | 7268 | 1.6-2.0 | 6.0-7.5 | 12 | † | 42 | 1600 | 105 | 6500 | |
| 10497123 | CS144 | 100 | N | 1G-291 | CW | 7270 | 1.7-2.1 | 5.7-7.1 | 12 | † | 50 | 1600 | 120 | 6500 | |

‡ At maximum operating speed.

† Voltmeter not needed for output check. Load battery with carbon pile to obtain maximum output. Refer to applicable Service Bulletin for test procedure.